

Product datasheet

Specifications



High power contactor. TeSys Giga. 3 pole (3NO). AC-3 <=440V 330A. standard version. 48...130V wide band AC/DC coil

LC1G330EHEN

Price: 34,458.09 ZAR

Main

Range	TeSys
Range Of Product	TeSys Giga
Product Or Component Type	Contactor
Device Short Name	LC1G
Contactor Application	Power switching Motor control
Utilisation Category	AC-1 AC-3 AC-3e AC-4 AC-5a AC-5b AC-6a AC-6b AC-8b AC-8a DC-1 DC-3 DC-5
Poles Description	3P
[Ue] Rated Operational Voltage	<= 1000 V AC 50/60 Hz <= 460 V DC
[Ie] Rated Operational Current	440 A (at <40 °C) at <= 1000 V AC-1 330 A (at <60 °C) at <= 440 V AC-3
[Uc] Control Circuit Voltage	48...130 V AC 50/60 Hz 48...130 V DC
Control Circuit Voltage Limits	Operational: 0.8 Uc Min...1.1 Uc Max (at <60 °C) Drop-out: 0.1 Uc Max...0.45 Uc Min (at <60 °C)

Complementary

[Uimp] Rated Impulse Withstand Voltage	8 kV
Overvoltage Category	III
[Ith] Conventional Free Air Thermal Current	440 A (at 40 °C)
Rated Breaking Capacity	2940 A at 440 V
[Icw] Rated Short-Time Withstand Current	2.65 kA - 10 s 1.8 kA - 30 s 1.3 kA - 1 min 0.9 kA - 3 min 0.75 kA - 10 min
Associated Fuse Rating	400 A aM at <= 440 V for motor 250 A aM at <= 690 V for motor 500 A gG at <= 690 V

Excluding VAT and subject to change. Please check with your local distributor through "Where to buy"

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Average Impedance	0.000144 Ohm
[Ui] Rated Insulation Voltage	1000 V
Power Dissipation Per Pole	30 W AC-1 - lth 440 A 16 W AC-3 - lth 330 A
Compatibility Code	LC1G
Pole Contact Composition	3 NO
Auxiliary Contact Composition	1 NO + 1 NC
Motor Power Kw	90 kW at 230 V AC 50/60 Hz (AC-3e) 160 kW at 400 V AC 50/60 Hz (AC-3e) 160 kW at 415 V AC 50/60 Hz (AC-3e) 185 kW at 440 V AC 50/60 Hz (AC-3e) 200 kW at 500 V AC 50/60 Hz (AC-3e) 220 kW at 690 V AC 50/60 Hz (AC-3e) 185 kW at 1000 V AC 50/60 Hz (AC-3e) 90 kW at 230 V AC 50/60 Hz (AC-3) 160 kW at 400 V AC 50/60 Hz (AC-3) 160 kW at 415 V AC 50/60 Hz (AC-3) 200 kW at 440 V AC 50/60 Hz (AC-3) 200 kW at 500 V AC 50/60 Hz (AC-3) 220 kW at 690 V AC 50/60 Hz (AC-3) 185 kW at 1000 V AC 50/60 Hz (AC-3) 90 kW at 230 V AC 50/60 Hz (AC-4) 160 kW at 400 V AC 50/60 Hz (AC-4) 160 kW at 415 V AC 50/60 Hz (AC-4) 185 kW at 440 V AC 50/60 Hz (AC-4) 200 kW at 500 V AC 50/60 Hz (AC-4) 220 kW at 690 V AC 50/60 Hz (AC-4) 185 kW at 1000 V AC 50/60 Hz (AC-4)
Motor Power Hp	100 hp at 200/208 V 60 Hz 125 hp at 230/240 V 60 Hz 250 hp at 460/480 V 60 Hz 300 hp at 575/600 V 60 Hz
Irms Rated Making Capacity	3830 A at 440 V
Coil Technology	Built-in bidirectional peak limiting
Mechanical Durability	8 Mcycles
Inrush Power In Va (50/60 Hz, Ac)	780 VA
Inrush Power In W (Dc)	695 W
Hold-In Power Consumption In Va (50/60 Hz, Ac)	17.6 VA
Hold-In Power Consumption In W (Dc)	7.8 W
Operating Time	40...70 ms closing 15...50 ms opening
Maximum Operating Rate	600 cyc/h AC-3 600 cyc/h AC-3e 300 cyc/h AC-1 150 cyc/h AC-4
Connections - Terminals	Power circuit: bar 2 - busbar cross section: 32 x 10 mm Power circuit: lugs-ring terminals 1 185 mm² Power circuit: bolted connection Control circuit: push-in 1 0.2...2.5 mm² - cable stiffness: solid stranded without cable end Control circuit: push-in 1 0.25...2.5 mm² - cable stiffness: flexible with cable end Control circuit: push-in 2 0.5...1.0 mm² with cable end Control circuit: push-in 0.75...2.5 mm² - cable stiffness: solid stranded without cable end Control circuit: push-in 0.75...2.5 mm² - cable stiffness: flexible with cable end
Connection Pitch	45 mm
Mounting Support	Plate

Standards	EN/IEC 60947-4-1 EN/IEC 60947-5-1 UL 60947-4-1 CSA C22.2 No 60947-4-1 JIS C8201-4-1 JIS C8201-5-1
Product Certifications	CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL
Tightening Torque	35 N.m
Height	225 mm
Width	140 mm
Depth	226 mm
Net Weight	7.5 kg

Environment

Ip Degree Of Protection	IP2X front face with shrouds conforming to IEC 60529 IP2X front face with shrouds conforming to VDE 0106
Ambient Air Temperature For Operation	-25...60 °C
Ambient Air Temperature For Storage	-60...80 °C
Mechanical Robustness	Vibrations 5...300 Hz 2 gn contactor open Vibrations 5...300 Hz 4 gn contactor closed Shocks 10 gn 11 ms contactor open Shocks 15 gn 11 ms contactor closed
Colour	Dark grey
Protective Treatment	TH
Permissible Ambient Air Temperature Around The Device	-40...70 °C at Uc

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	31.0 cm
Package 1 Width	22.5 cm
Package 1 Length	31.5 cm
Package 1 Weight	7.481 kg
Unit Type Of Package 2	S06
Number Of Units In Package 2	4
Package 2 Height	105 cm
Package 2 Width	60 cm
Package 2 Length	80 cm
Package 2 Weight	39.924 kg

Sustainability

Green Premium™ label is Schneider Electric’s commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product’s sustainability >](#)



Transparency RoHS/REACH

Well-being performance

✓	Mercury Free	
✓	Rohs Exemption Information	Yes
✓	Pvc Free	
✓	Halogen Free Plastic Parts Product	

Certifications & Standards

Reach Regulation	REACH Declaration
Eu Rohs Directive	Compliant with Exemptions
China Rohs Regulation	China RoHS declaration
Environmental Disclosure	Product Environmental Profile
Circularity Profile	End of Life Information

Installation

Installation Videos

- [TeSys Giga - How to install the auxiliary contact block](#)
- [TeSys Giga - How to install and remove remote wear diagnosis module](#)
- [TeSys Giga - How to install mechanical interlock kit](#)
- [TeSys Giga - How to install cable memory kit](#)
- [TeSys Giga - How to directly mount LR9G overload relay](#)
- [TeSys Giga - How to replace control module](#)
- [TeSys Giga - How to replace switching modules](#)
- [TeSys Giga - How to assemble reverser solution](#)
- [TeSys Giga - How to assemble change-over solution](#)