

# Product datasheet

Specifications



cord set - 40-way terminal - 1 x  
HE10 connector - for M340 I/O - 10  
m

BMXFCC1001

⚠ Discontinued on: 07 Aug 2023

⚠ Discontinued

Price: 4,303.26 ZAR

## Main

|                                       |                                                        |
|---------------------------------------|--------------------------------------------------------|
| Range Of Product                      | Modicon X80                                            |
| Accessory / Separate Part Type        | Preformed cordset                                      |
| Accessory / Separate Part Designation | Preformed cordset for Telefast Advantys ABE7 sub-bases |
| Accessory / Separate Part Destination | For I/O module with 40-way connectors                  |
| Number Of Cables                      | 1                                                      |
| Electrical Connection                 | 1 connector 40 ways<br>1 connector HE10                |
| Cable Length                          | 10 m                                                   |

## Complementary

|                       |                       |
|-----------------------|-----------------------|
| Total Number Of Wires | 20                    |
| Wire Section          | 0.324 mm <sup>2</sup> |
| Net Weight            | 2.78 kg               |

## Packing Units

|                              |           |
|------------------------------|-----------|
| Unit Type Of Package 1       | PCE       |
| Number Of Units In Package 1 | 1         |
| Package 1 Height             | 6.000 cm  |
| Package 1 Width              | 26.000 cm |
| Package 1 Length             | 28.000 cm |
| Package 1 Weight             | 1.495 kg  |
| Unit Type Of Package 2       | S02       |
| Number Of Units In Package 2 | 4         |
| Package 2 Height             | 15.000 cm |
| Package 2 Width              | 30.000 cm |
| Package 2 Length             | 40.000 cm |
| Package 2 Weight             | 5.980 kg  |

## Contractual warranty

|          |           |
|----------|-----------|
| Warranty | 18 months |
|----------|-----------|

Excluding VAT and subject to change. Please check with your local distributor through "Where to buy"

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

# Sustainability

**Green Premium™ label** is Schneider Electric’s commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product’s sustainability >](#)



Transparency

## Well-being performance

|                              |                                                                                                   |
|------------------------------|---------------------------------------------------------------------------------------------------|
| ✓ Toxic Heavy Metal Free     |                                                                                                   |
| ✓ Mercury Free               |                                                                                                   |
| ✓ Rohs Exemption Information | Yes                                                                                               |
| Eu Rohs Directive            | Pro-active compliance (Product out of EU RoHS legal scope)<br><a href="#">EU RoHS Declaration</a> |
| China Rohs Regulation        | <a href="#">China RoHS declaration</a>                                                            |
| Environmental Disclosure     | <a href="#">Product Environmental Profile</a>                                                     |
| Circularity Profile          | No need of specific recycling operations                                                          |