

Product datasheet

Specifications



Bare cable connector, GoPact MCCB 250, 3 poles

G25SBC3P

Main

Range Of Product	GoPact MCCB
Product Or Component Type	Bare cable connector
Device Application	Connection
Range Compatibility	GoPact MCCB 250
Poles Description	3P
Quantity	6

Complementary

Localisation On Device	Upstream Downstream
[In] Rated Current	250 A
Conductor Material	Steel
Connections - Terminals	Clamp cage (cable) 50...150 mm ² flexible Clamp cage (cable) 50...185 mm ² rigid

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	4.5 cm
Package 1 Width	9.5 cm
Package 1 Length	13.5 cm
Package 1 Weight	385 g
Unit Type Of Package 2	S02
Number Of Units In Package 2	10
Package 2 Height	15 cm
Package 2 Width	30 cm
Package 2 Length	40 cm
Package 2 Weight	4.165 kg
Unit Type Of Package 3	P06
Number Of Units In Package 3	160
Package 3 Height	60 cm
Package 3 Width	60 cm

Excluding VAT and subject to change. Please check with your local distributor through "Where to buy"

Package 3 Length	80 cm
Package 3 Weight	75.14 kg

Sustainability

Green Premium™ label is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product's sustainability >](#)

Well-being performance

✓ Reach Free Of Svhc

✓ Mercury Free

✓ Rohs Exemption Information [Yes](#)

✓ Pvc Free

Reach Regulation [REACH Declaration](#)

Eu Rohs Directive Compliant
[EU RoHS Declaration](#)

China Rohs Regulation [China RoHS declaration](#)
Pro-active China RoHS declaration (out of China RoHS legal scope)

Weee The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins
