

Product datasheet

Specifications



control power disconnect module

LUA8E20

Price: 714.39 ZAR

Main

Range	TeSys
Device Short Name	LUA8
Product Or Component Type	Auxiliary contact

Complementary

Auxiliary Contact Composition	2 NO
Signalling Function	Start-stop
[Ue] Rated Operational Voltage	690 V AC 690 V DC
[Ith] Conventional Free Air Thermal Current	5 A
Minimum Switching Voltage	17 V
Minimum Switching Current	80 mA
Net Weight	0.048 kg
Connections - Terminals	Screw clamp terminals

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	1.5 cm
Package 1 Width	11.0 cm
Package 1 Length	8.8 cm
Package 1 Weight	60.0 g
Unit Type Of Package 2	S02
Number Of Units In Package 2	50
Package 2 Height	15.0 cm
Package 2 Width	30.0 cm
Package 2 Length	40.0 cm
Package 2 Weight	3.36 kg

Contractual warranty

Warranty	18 months
----------	-----------

Excluding VAT and subject to change. Please check with your local distributor through "Where to buy"

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Sustainability

Green Premium™ label is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product's sustainability >](#)

Well-being performance

✓	Reach Free Of Svhc	
✓	Toxic Heavy Metal Free	
✓	Mercury Free	
✓	Rohs Exemption Information	Yes
Reach Regulation	REACH Declaration	
Eu Rohs Directive	Compliant	EU RoHS Declaration
China Rohs Regulation	China RoHS declaration	
Weee	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins	